

Clear

Removes all data leaving blank records.

Syntax

```
rv = Send_Message(Ctrl, "OLE.Clear", Fill)
```

Parameters

Parameter	Description
Fill	2 to simply clear the table; 1 to fill the cleared table with as many new records as will fit; 0 to leave only one blank record

Remarks

The Clear method is a convenient way to reset an SRP OLE Edit Table control. To leave one blank records, set the Fill parameter to 0. To leave enough blank records to fill the table's visible space, set the Fill parameter to 1. To just clear the table without affecting the number of rows, set the Fill parameter to 2. In either case, the SelPos is always moved back to the top left most selectable

Example

```
// Clear the table leaving only one blank records  
rv = Send_Message(Ctrl, "OLE.Clear", 0)  
  
// Clear the table filling the table with blank records  
rv = Send_Message(Ctrl, "OLE.Clear", 1)  
  
// Clear the table leaving the number of rows alone  
rv = Send_Message(Ctrl, "OLE.Clear", 2)
```